

# DEDICATED AMPLIFICATION



160W 8Ω 320W 4Ω DISCRETE CIRCUIT

STEREO, DUAL MONO, OR BRIDGED

CLASS AB TRUE DUAL
MONO DESIGN





# LUMÍN

THE PERFECT PARTNER TO YOUR
LUMIN MUSIC PLAYER

CNC SINGLE BILLET ALUMINIUM CONSTRUCTION

160W PER CHANNEL INTO 8Ω 320W PER CHANNEL INTO 4Ω

TRUE DUAL MONO POWER SUPPLY AND AMPLIFIER DESIGN

**CLASS AB AMPLIFICATION** 

STEREO, DUAL MONO AND BRIDGED MODE OPERATION

FULLY DISCRETE VOLTAGE AND CURRENT GAIN STAGES

DC, OVERLOAD AND OVERHEATING PROTECTION

BESPOKE 600VA TOROIDAL TRANSFORMER



**OPERATING MODE** (selectable) Stereo, Dual Mono or Bridged mode

INPUT (selectable)
1 x XLR pair (pin 2 hot), 1 x RCA pair

# **POWER**

160W per channel into  $8\Omega$  320W per channel into  $4\Omega$  640W into  $8\Omega$  (Bridged)

# **POWER SUPPLY**

Available in 220–240V AC and 110–120V AC versions ~ 50/60Hz

# POWER CONSUMPTION

Standby <0.5W Idle 40W Max 700W

# FREQUENCY RESPONSE

20hz - 40000hz ± 0.1db Signal to Noise Ratio 103db, unweighted

# INPUT IMPEDANCE

200k $\Omega$  Balanced (XLR) 100k $\Omega$  Unbalanced (RCA)

# OUTPUT IMPEDANCE

0.1Ω

# INPUT SENSITIVITY

1.16Vrms

# GAIN

- +26dB (Stereo, Dual Mono)
- +32dB (Bridged)

# **PROTECTION**

DC, overload and overheating protection

# FINISHES

Black anodized brushed aluminium or Raw brushed aluminium

# CONSTRUCTION

CNC-machined from a single billet for front, top and sides. Thick 8mm walls, rear panel and base plate

PHYSICAL: 350mm (W), 374mr (D), 104mm (H), 19kg

WWW.LUMINMUSIC.COM